

## Horus Emergency Exit Sign

Our ultra-slim 2.8W modern LED exit sign brings the efficiency and flexibility of LED to the vital sector of emergency lighting and has a neat picture frame appearance when compared to conventional bulky exit signs.

With its 2.8 Watt LED light source, it provides a daylight 6,500k illumination across the legend with 5 individual LEDs providing downlight.

This item is supplied with all legend options (down, left and right) and this self-illuminating exit sign can be clearly seen in emergency situations and at 24m.



### Specification

<b>Colour Temperature</b>	6500K
<b>Watts:</b>	2.8W
<b>Guarantee</b>	3 years
<b>Luminaire</b>	SMT 2835 LED*5PCS / SMT 3014 LED*20PCS
<b>Power Factor</b>	0.3
<b>Supply Current</b>	40Ma
<b>IP Rating</b>	IP20
<b>Operating Temperature</b>	0°C- 40°C
<b>Voltage</b>	50/60Hz.
<b>Emergency Duration</b>	180 minutes
<b>Battery Installed or Replaced</b>	3.6V 800mAh
<b>Fuse Installed or Replaced</b>	1A/3 15A 250V
<b>Recharge time</b>	24 hours
<b>Viewing Distance</b>	24m

#### Product

Horus 2.8W Slimline Emergency Exit Sign

#### Code

SLLHES

L I F E . I L L U M I N A T E D